Active Clamp Silicon N-channel MOSFET

AEC-Q101 Compliance

DESCRIPTION


INKA214AP1 is a Silicon N-channel Active Clamp MOSFET. The built in clamp diode connected between drain and gate protects the MOS-FET from the counter electromotive force in switching drive of the inductance load.

FEATURE

- •The built in clamp diode connected between drain and gate.
- •Built in bias resistor enables reduction of parts count.
- Drive voltage 4V

APPLICATION


Motor, Solenoid drive etc




MAXIMUM RATINGS (Ta=25°C)

Symbol	Parameter	Rating	Unit	
Vgss	Gate-Source Voltage	10	٧	
ĪD	Drain Current(DC)	2(※1)	Α	
I DP	Drain Current(Pulse)	6(※2)	Α	
Pb	Total Power Dissipation	0.75(※1)	W	
Tch	Channel Temperature	+150	°C	
Tstg	Storage temperature	−55 ~ +150	°C	

32 Pw≤1ms , Duty cycle≤1%







ELECTRICAL CHARACTERISTICS (Ta=25°C)


Parameter	Symbol	Test Condition		Limit		
Parameter			MIN	TYP	MAX	Unit
Drain-Source Breakdown Voltage	$V_{(BR)DSS}$	I _D =10mA, V _{GS} =0V	38	-	62	٧
Gate-Source Leak current	I_{GSS}	$V_{GS}=\pm 5V$, $V_{DS}=0V$	-	-	±100	μΑ
Zero Gate Voltage Drain Current	I _{DSS}	V _{DS} =30V ,V _{GS} =0V	-	-	1.0	μΑ
Gate Threshold Voltage	V_{th}	I _D =1mA, V _{DS} = V _{GS}	1.0	-	2.5	V
Forward Transfer Admittance	Y _{fs}	V _{DS} =10V, I _D =1A	-	2	-	S
Chatic Dunin Course On Chata Danishana	В	I _D =1A, V _{GS} =10V	-	150	-	mΩ
Static Drain-Source On-State Resistance	R _{DS(ON)}	I _D =1A, V _{GS} =4.5V	-	200	-	mΩ
Gate-Source Resistance	R_{gs}		-	100	-	kΩ
Gate Resistance1	R _g (1)		-	1.5	-	kΩ
Gate Resistance2	R _g (2)		-	500	-	Ω
Input Capacitance	C _{iss}	V 10V V 0V 5 11VI	-	20	-	pF
Output Capacitance	Coss	V_{DS} =10V, V_{GS} =0V, f=1MHz	-	55	-	pF
Control in a Time	t _{on}	V _{DD} =30V, I _D =1A V _{GS} =0∼10V	-	2.8	-	μs
Switching Time	t _{off}		-	0.8	_	μs


Active Clamp Silicon N-channel MOSFET


TYPICAL CHARACTERISTICS


















Active Clamp Silicon N-channel MOSFET




Active Clamp Silicon N-channel MOSFET








Switching time test condition





Keep safety first in your circuit designs!

ISAHAYA Electronics Corporation puts the maximum effort into making semiconductor products better and more reliable, but there is always the possibility that trouble may occur with them. Trouble with semiconductors may lead to personal injury, fire or property damage. Remember to give due consideration to safety when making your circuit designs, with appropriate measures such as (1) placement of substitutive, auxiliary, (2) use of non-farmable material or (3) prevention against any malfunction or mishap.

Notes regarding these materials

- •These materials are intended as a reference to our customers in the selection of the ISAHAYA products best suited to the customer's application; they don't convey any license under any intellectual property rights, or any other rights, belonging ISAHAYA or third party.
 •ISAHAYA Electronics Corporation assumes no responsibility for any damage, or infringement of any third party's rights, originating in the use of any product data, diagrams, charts or circuit application examples contained in these materials.
- All information contained in these materials, including product data, diagrams and charts, represent information on products at the time of publication of these materials, and are subject to change by ISAHAYA Electronics Corporation without notice due to product improvements or other reasons. It is therefore recommended that customers contact ISAHAYA Electronics Corporation or an authorized ISAHAYA products distributor for the latest product information before purchasing product listed herein.
- distributor for the latest product information before purchasing product listed herein.

 ISAHAYA Electronics Corporation products are not designed or manufactured for use in a device or system that is used under circumstances in which human life is potentially at stake. Please contact ISAHAYA Electronics Corporation or an authorized ISAHAYA products distributor when considering the use of a product contained herein for any specific purposes, such as apparatus or systems for transportation, vehicular, medical, aerospace, nuclear, or undersea repeater use.
- The prior written approval of ISAHAYA Electronics Corporation is necessary to reprint or reproduce in whole or in part these materials.
- If these products or technologies are subject to the Japanese export control restrictions, they must be exported under a license from the Japanese government and cannot be imported into a country other than the approved destination. Any diversion or re-export contrary to the export control laws and regulations of Japan and/or the country of destination is prohibited.
- Please contact ISAHAYA Electronics Corporation or authorized ISAHAYA products distributor for further details on these materials or the products contained therein.