2SC3928A

FOR LOW FREQUENCY AMPLIFY APPLICATION SILICON NPN EPITAXIAL TYPE

DESCRIPTION

2SC3928A is super mini package resin sealed silicon NPN epitaxial transistor,

It is designed for low frequency voltage application.

Complementary with ISA1530AC1.

FEATURE


- Small collector to emitter saturation voltage.
 - VCE(sat)=0.3V max
- Excellent linearity of DC forward gain.
- Super mini package for easy mounting


APPLICATION

For Hybrid IC, small type machine low frequency voltage Amplify application.

MAXIMUM RATINGS (Ta=25°C)

Parameter	Symbol	Ratings	Unit
Collector to Base voltage	V _{CBO}	50	٧
Collector to Emitter voltage	V _{CEO}	50	٧
Emitter to Base voltage	V _{EBO}	6	٧
Collector current	I _C	200	mA
Collector dissipation	Pc	200	mW
Junction temperature	T _j	+150	°C
Storage temperature	T_{stg}	-55 ~ +150	°C





ELECTRICAL CHARACTERISTICS(Ta=25°C)

Parameter	Symbol	Took on divino	Limits			Unit
		Test conditions	Min	Тур	Max	Unit
C to E breakdown voltage	V(BR)CEO	Ic=100 μ A,R _{BE} =∞	50	_	_	٧
Collector cut off current	Ісво	Vcb=50V,IE=0	_	_	0.1	μΑ
Emitter cut off current	І ЕВО	V _{EB} =4V,I _C =0	ı	_	0.1	μΑ
DC forward current gain	hFE1	VcE=6V,Ic=1mA	120	(※)	560	ı
DC forward current gain	hFE2	VcE=6V,Ic=0.1mA	70	_	_	ı
C to E Saturation Voltage	VCE(sat)	Ic=100mA,IB=10mA	ı	_	0.3	٧
Gain bandwidth product	fT	VcE=6V,IE=-10mA	1	200	_	MHz
Collector output capacitance	Cob	VcB=6V,IE=0,f=1MHz	_	4	_	pF
Noise Figure	NF	Vc==6V,Ie==0.1mA,f=1kHz,Rg=2k Ω	_	_	15	dB


X: It shows hFE classification at right table.

Item	Q	R	S
hFE	120~270	180~390	270~560

2SC3928A

FOR LOW FREQUENCY AMPLIFY APPLICATION SILICON NPN EPITAXIAL TYPE

TYPICIAL CHARACTERISTICS





Keep safety first in your circuit designs!

-ISAHAYA Electronics Corporation puts the maximum effort into making semiconductor products better and more reliable, but there is always the possibility that trouble may occur with them. Trouble with semiconductors may lead to personal injury, fire or property damage. Remember to give due consideration to safety when making your circuit designs, with appropriate measures such as (1) placement of substitutive, auxiliary, (2) use of non-farmable material or (3) prevention against any malfunction or mishap.

Notes regarding these materials

- -These materials are intended as a reference to our customers in the selection of the ISAHAYA products best suited to the customer's application; they don't convey any license under any intellectual property rights, or any other rights, belonging ISAHAYA or third party. ISAHAYA Electronics Corporation assumes no responsibility for any damage, or infringement of any third party's rights, originating in the use of any product data, diagrams, charts or circuit application examples contained in these materials.
- All information contained in these materials, including product data, diagrams and charts, represent information on products at the time of publication of these materials, and are subject to change by ISAHAYA Electronics Corporation without notice due to product improvements or other reasons. It is therefore recommended that customers contact ISAHAYA Electronics Corporation or an authorized ISAHAYA products distributor for the latest product information before purchasing product listed herein.
- ISAHAYA Electronics Corporation products are not designed or manufactured for use in a device or system that is used under circumstances in which human life is potentially at stake. Please contact ISAHAYA Electronics Corporation or an authorized ISAHAYA products distributor when considering the use of a product contained herein for any specific purposes, such as apparatus or systems for transportation, vehicular, medical, aerospace, nuclear, or undersea repeater use.
- The prior written approval of ISAHAYA Electronics Corporation is necessary to reprint or reproduce in whole or in part these materials.
- If these products or technologies are subject to the Japanese export control restrictions, they must be exported under a license from the Japanese government and cannot be imported into a country other than the approved destination. Any diversion or re-export contrary to the export control laws and regulations of Japan and/or the country of destination is prohibited.
- Please contact ISAHAYA Electronics Corporation or authorized ISAHAYA products distributor for further details on these materials or the products contained therein.