RT1P240X SERIES

〈Transistor〉

Transistor With Resistor

For Switching Application

Silicon PNP Epitaxial Type

DESCRIPTION

RT1P240X is a one chip transistor
with built-in bias resistor,NPN type is RT1N240X.

FEATURE

・Built-in bias resistor (R1=22kΩ).

APPLICATION

. Inverted circuit,switching circuit,interface circuit,driver circuit.

Equivalent circuit



OUTLINE DRAWING

UNIT : mm

RT1P240C



JEITA : SC-59
JEDEC : Similar to TO-236

Terminal Connector
①:Base
②:Emitter
③:Collector

RT1P240U



JEITA : SC-75A
JEDEC : —

Terminal Connector
①:Base
②:Emitter
③:Collector

RT1P240M



JEITA : SC-70
JEDEC : —

Terminal Connector
①:Base
②:Emitter
③:Collector

RT1P240S



JEITA : —
JEDEC : —

Terminal Connector
①:Emitter
②:Collector
③:Base

RT1P240X SERIES

〈Transistor〉

Transistor With Resistor

For Switching Application

Silicon PNP Epitaxial Type

MARKING

RT1P240C RT1P240M RT1P240U	RT1P240S
	

MAXIMUM RATING (Ta=25℃)

SYMBOL	PARAMETER	RATING				UNIT
		RT1P240U	RT1P240M	RT1P240C	RT1P240S	
V_{CBO}	Collector to Base voltage	−50				V
V_{EBO}	Emitter to Base voltage	−6				V
V_{CEO}	Collector to Emitter voltage	−50				V
I_C	Collector current	−100				mA
I_{CM}	Peak Collector current	−200				mA
P_C	Collector dissipation(Ta=25℃)	150	200		450	mW
Tj	Junction temperature	+150				℃
Tstg	Storage temperature	−55～+150				℃

ELECTRICAL CHARACTERISTICS (Ta=25℃)

SYMBOL	PARAMETER	TEST CONDITION	LIMIT			UNIT
			MIN	TYP	MAX	
$V_{(BR)CEO}$	C to E break down voltage	I_C=−100μA, R_{BE}=∞	−50	—	—	V
I_{CBO}	Collector cut off current	V_{CB}=−50V, I_E=0	—	—	−0.1	μA
I_{EBO}	Emitter cut off current	V_{EB}=−5V, I_C=0	—	—	−0.1	μA
h_{FE}	DC forward current gain	V_{CE}=−5V, I_C=−1mA	100	—	—	—
$V_{CE(sat)}$	C to E saturation voltage	I_C=−10mA, I_B=−0.5mA	—	—	−0.3	V
R_1	Input resistor	—	15	22	29	kΩ
f_T	Gain band width product	V_{CE}=−6V, I_E=10mA	—	150	—	MHz

RT1P240X SERIES

〈Transistor〉

Transistor With Resistor

For Switching Application

Silicon PNP Epitaxial Type

TYPICAL CHARACTERISTICS (Ta=25℃)

COLLECTOR DISSIPATION
VS AMBIENT TEMPERATURE



DC FORWARD CURRENT GAIN
VS COLLECTOR CURRENT



INPUT ON VOLTAGE
VS COLLECTOR CURRENT



COLLECTOR CURRENT
VS INPUT OFF VOLTAGE



COLLECTOR TO EMITTER SATURATION
VOLTAGE VS COLLECTOR CURRENT



ISAHAYA ELECTRONICS CORPORATION

Keep safety first in your circuit designs!

·ISAHAYA Electronics Corporation puts the maximum effort into making semiconductor products better and more reliable, but there is always the possibility that trouble may occur with them. Trouble with semiconductors may lead to personal injury, fire or property damage. Remember to give due consideration to safety when making your circuit designs, with appropriate measures such as (1) placement of substitutive, auxiliary, (2) use of non-farmable material or (3) prevention against any malfunction or mishap.

Notes regarding these materials

·These materials are intended as a reference to our customers in the selection of the ISAHAYA products best suited to the customer’ s application; they don't convey any license under any intellectual property rights, or any other rights, belonging ISAHAYA or third party.

·ISAHAYA Electronics Corporation assumes no responsibility for any damage, or infringement of any third party's rights, originating in the use of any product data, diagrams, charts or circuit application examples contained in these materials.

·All information contained in these materials, including product data, diagrams and charts, represent information on products at the time of publication of these materials, and are subject to change by ISAHAYA Electronics Corporation without notice due to product improvements or other reasons. It is therefore recommended that customers contact ISAHAYA Electronics Corporation or an authorized ISAHAYA products distributor for the latest product information before purchasing product listed herein.

·ISAHAYA Electronics Corporation products are not designed or manufactured for use in a device or system that is used under circumstances in which human life is potentially at stake. Please contact ISAHAYA Electronics Corporation or an authorized ISAHAYA products distributor when considering the use of a product contained herein for any specific purposes, such as apparatus or systems for transportation, vehicular, medical, aerospace, nuclear, or undersea repeater use.

·The prior written approval of ISAHAYA Electronics Corporation is necessary to reprint or reproduce in whole or in part these materials.

·If these products or technologies are subject to the Japanese export control restrictions, they must be exported under a license from the Japanese government and cannot be imported into a country other than the approved destination. Any diversion or re-export contrary to the export control laws and regulations of Japan and/or the country of destination is prohibited.

·Please contact ISAHAYA Electronics Corporation or authorized ISAHAYA products distributor for further details on these materials or the products contained therein.